

ENWALK™
Towards Future

Brighto

116/116A/116Li

RECHARGEABLE
24X7 LED LIGHT



With Mobile
Charging

80%

Energy
Saving



12 *upto
Hours of
backup



12 Months
Warranty

Technical Specifications

	BRIGHTO 116	BRIGHTO 116 A	BRIGHTO 116 Li
Adaptor	5.5 V-500mA	7.8 V-500mA	5.5 V-500mA
Lantern Wattage	1.7 watts	1.7 watts	1.7 watts
Number of LEDs	Flash Light: 1(0.5W) 180° Rotating Light: 24	Flash Light: 1(0.5W) 180° Rotating Light: 24	Flash Light: 1(0.5W) 180° Rotating Light: 24
Back-up Time Expected ***			
High Mode-Full Brightness	8 Hours	15 Hours	8 Hours
Low Mode-Medium Brightness	12 Hours	-	12 Hours
Flash Mode	24 Hours	40 Hours	24 Hours
Mobile Charging O/P with USB	-	5.5 V/350mA	5.5 V/350mA
Battery	Lead Acid 4V/4.5Ah	Lead Acid 6V/4.5Ah	Lithium Ion 3.7V/4.4Ah
Recharge Time (Time needed to charge battery)	8 Hours	6-8 Hours	8 Hours
Temperature Rating (Ambient)	- 5 to 50° Celsius	- 5 to 50° Celsius	- 5 to 50° Celsius
Indicator	3 Color Indicator Orange-Mobile Chg. Green- Battery Chg. Red- Battery Low	On Unit Red-Chg. ON/Power ON/OFF On Adaptor Red-Battery Chg. ON Green-Battery Chg. Full	3 Color Indicator Orange-Mobile Chg. Green-Battery Chg. Red- Battery Low

*** Back-up Time reduces if Mobile is used

Special Features

- Sliding Switch / Single Touch Button for Multi Functions.
- In-Built Mobile Charging System.
- Mains SMPS Adaptor provided.
- In-Built Lead Acid / Lithium Ion Battery System.
- Three Levels Lighting possible for energy conservation.
- Lights and Mobile Charging Function on while charging, so truly 24/7 availability.
- Battery Cut Out for ensuring Minimum Lighting availability.

Sales Inquiry:

enwalk@auraeco.com

Manufactured & Marketed by:

Arham Electronics & Electricals

Pune 411 041, Maharashtra, India.

Tel.: +91-9922999720, 9822030258

www.enwalk.com